

Programmed Timer Relays Units

Relay Temporizzati Programmati

Delay OFF Falling Input Timer Relay With Reset

OUR CODE	V	OPERATING VOLTAGE	RATED LOAD	MAX SWITCHING VOLTAGE	FUNCTION DIAGRAM
T.35.205.T1	12	9-15V	25A (87) /20A	12VDC	
T.35.205.T1M	12	9-15V	25A (87) /20A	12VDC	
T.35.405.T1	24	18-30V	15A (87) /10A	24VDC	
T.35.405.T1M	24	18-30V	15A (87) /10A	24VDC	

The bulb/application switch to OFF after a programmed time, timing starts after the input trigger is removed. **T1** from 0,5 seconds to 120 seconds. **T1M** from 0,5 minutes to 120 minutes. (A new impulse trigger will reset the timing).

Il bulbo/l'applicazione si spegne trascorso il ritardo programmato (T1). Il conteggio inizia quando il segnale di attivazione viene rimosso. **T1** da 0,5 secondi a 120 secondi. **T1M** da 0,5 minuti a 120 minuti. (Un nuovo impulso di attivazione resetta il conteggio).