

Programmed Timer Relays Units

Relay Temporizzati Programmati

Delay ON and Delay OFF Timer Relay

OUR CODE	V	OPERATING VOLTAGE	RATED LOAD	MAX SWITCHING VOLTAGE	FUNCTION DIAGRAM
T.38.205.T1.T2	12	9-15V	25A (87) /20A	12VDC	
T.38.205.T1M.T2M	12	9-15V	25A (87) /20A	12VDC	
T.38.405.T1.T2	24	18-30V	15A (87) /10A	24VDC	
T.38.405.T1M.T2M	24	18-30V	15A (87) /10A	24VDC	

The bulb/application switch to ON after the programmed time **T1**. Timing starts when the input trigger is applied.
The bulb/application switch to OFF after the programmed time **T2**. Timing starts when the input trigger is removed.

T1 from 10ms to 2,5 seconds. **T1M** from 0,5 seconds to 120 seconds.
T2 from 10ms to 2,5 seconds. **T2M** from 0,5 seconds to 120 seconds.

Il bulbo/l'applicazione si accende trascorso il ritardo programmato **T1**. Il conteggio inizia quando si applica il segnale di attivazione.
Il bulbo/applicazione si spegne trascorso il ritardo programmato **T2**. Il conteggio inizia quando il segnale di attivazione viene rimosso.

T1 da 10ms a 2,5 secondi. **T1M** da 0,5 secondi a 120 secondi. **T2** da 10ms a 2,5 secondi. **T2M** da 0,5 secondi a 120 secondi.